# Hall effect spool position sensors

- SPSD type
- SPSL type

### **Spool position sensors**


Accuracy, reliability and repeatability are the main features of Walvoil position sensors. Converts the spool movements into an electric digital signal or into a voltage linear signal.

Working conditions	SPSD	SPSD-S	SPSL	SPSL-S	
Voltage supply	from 9 to 32 VDC		from 9 to 32 VDC or 5 VDC		
Current absorption	< 10 mA	(no load)	< 10 mA (no load)		
Mechanical life	3x	10 <sup>6</sup>	3x10 <sup>6</sup>		
Connector type	DT04-4F	Deutsch	DT04-4P Deutsch		
Weather protection	IP67 /	IP67 / IPX9K		IP67 / IPX9K	
Working temperature	from -40°C to 105°C (from -40°F to 221°F)		from -40°C to 105°C (from -40°F to 221°F)		
Working pressure	350 bar <i>(5100 psi)</i>		350 bar <i>(5100 psi)</i>		
Max. electrical stroke	±10 mm (±0.39 in)	±5.5 mm (±0.22 in)	±10 mm (±0.39 in) ±5.5 mm (±0.22		
Max. mechanical stroke	±10 mm (±0.39 in)	±5.5 mm (±0.22 in)	±10 mm (±0.39 in)	±5.5 mm (±0.22 in)	
EMC compatibility	ISO 13766	/ ISO 14982	ISO 13766	/ ISO 14982	
Mechanical vibrations, shock, bumps	IEC 68-2-6,-27,-29		IEC 68-2-6,-27,-29		
Output signal type	PNP		/		
max. current	6 mA		/		
range	1		from 0.5 to 4.5 V		
linearity	/		± 5%		
spool in neutral	/		2.5 ± 0.2 V		
max. current	/		1 mA		

# **Spool position sensors**

### Hall effect spool position sensors

### **SPSD** type



The SPSD position sensor converts the spool movements into an electric digital signal.


Main features are:

- contactless technology guarantees a long mechanichal life;
- available for the complete range of valves.

Typical applications:

- cranes
- telehandlers
- aerial platforms
- front-end loaders (mid-mount)

## Output signal (SPSD example) vs. spool stroke




— out A


– out B

SPSL ordering codes				
Code	Description	Electrical stroke	Mechanical stroke	Supply
5SE210021D01	SPSD/M1021/PNP/D4P/v1.0	±10 mm (±0.39 in)	±10 mm (±0.39 in)	from 8 to 32 V
5SE310021D01	SPSD-S/M1021/PNP/D4P/V1.0	±10 mm (+0.39 in)	±10 mm (+0.39 in)	from 8 to 32 V


# Mating connector Code Type

5CON140072 DT06-4S Deutsch






A = feeler neutral position. As for the sensor model, the dimension can be 16 or 21.5 mm (0.63 or 0.85 in)



*	mm	in
SPSD	35	1.38
SPSD-S	31	1.22

Connector PIN-OUT		
Functions		
Out A		
GND		
VB+		
Out B		

# Example of sensor in 8EZ control with DPX100 working section






These controls, in different configurations, are available on the full range of Walvoil directional valves.

sectional valves.

# **Spool position sensors**

### Hall effect spool position sensors

### **SPSL** type



The SPSL position sensor converts the spool movements into a linear voltage signal.


### Main features are:

- contactless technology guarantees a long mechanichal life;
- available for the complete range of valves.

### Typical applications:

- cranes
- telehandlers
- · aerial platforms
- front-end loaders (mid-mount)

# Output signal (SPSL example) vs. spool stroke



SPSL ordering codes				
Code	Description	Electrical stroke	Mechanical stroke	Supply
5SE221021D01	SPSL/0.5(OUT)-4.5(IN)-CR10	±10 mm (±0.39 in)	±10 mm (±0.39 in)	5 V
5SE225516D01	SPSL/0.5(OUT)-4.5(IN)-CR5.5	±5.5 mm (±0.22 in)	±10 mm (±0.39 in)	5 V
5SE226516D01	SPSL/0.5(OUT)-4.5(IN)-CR6.5	±6.5 mm (±0.26 in)	±6.5 mm (±0.26 in)	5 V
5SE227021D01	SPSL/0.5(OUT)-4.5(IN)-CR7	±7 mm (±0.27 in)	±10 mm (±0.39 in)	5 V
5SE228021D01	SPSL/0.5(OUT)-4.5(IN)-CR8	±8 mm (±0.31 in)	±10 mm (±0.39 in)	5 V
5SE236521D01	SPSL/8-32V/0.5(OUT)-4.5(IN)	±6.5 mm (±0.26 in)	±10 mm (±0.39 in)	from 8 to 32 V
5SE325521D01	SPSL-S/0.5(OUT)-4.5(IN)-CR5.5	±5.5 mm (±0.22 in)	±10 mm (±0.39 in)	5 V

# Mating connector Code Type 5CON140072 DT06-4S Deutsch

A = feeler neutral position. As for the sensor model, the dimension can be 16 or 21.5 mm  $(0.63 \ or \ 0.85 \ in)$ 


	35 1.38 56 2.20
*	

Connector PIN-OUT			
	Errmotio		

mm in

Connector PIN-OUT			
Functions			
5V supply	8-32V supply		
+ 5V	signal OUT		
not connected	GND		
GND	VB+		
signal OUT	not connected		
	<b>5V supply</b> + 5V not connected GND		

# Example of sensor in 8EZ control with DPX100 working section



**IMPORTANT**: It is suggested to order the sensors through the controls assembled on the monoblock and sectional valves.

These controls, in different configurations, are available on the full range of Walvoil directional valves.